

8. Find the power spectral density of the random process $\{X(t)\}$ whose auto correlation is $R(\tau) = \begin{cases} -1; & -3 < \tau < 3 \\ 0; & \text{otherwise} \end{cases}$
9. When a system is said to be stable?
10. Assume that the input $X(t)$ to a linear time - invariant system is white noise. What is the power spectral density of the output process $Y(t)$ if the system response $H(\omega)$ is $H(\omega) = \begin{cases} 1 & \omega_1 < |\omega| < \omega_2 \\ 0 & \text{otherwise} \end{cases}$

PART B — (5 × 16 = 80 marks)

11. (a) (i) If the probability of success is $\frac{1}{100}$, how many trials are necessary in order that the probability of atleast one success is greater than $\frac{1}{2}$? (8)
- (ii) Find the moment generating function of Gamma distribution, with one parameter K and hence find its mean and variance. (8)

Or

- (b) (i) A and B shoot independently until each has his own target. The probability of their hitting the target at each shot is $\frac{3}{5}$ and $\frac{1}{4}$ respectively? Find the probability that B will require more shots than A . (8)
- (ii) If $\log_e^2 x$ is normally distributed with mean 1 and variance 4, find $P(\frac{1}{2} < x < 2)$ given that $\log_e^2 2 = 0.693$. (8)
12. (a) (i) Given the following bivariate probability distribution obtain
 (1) Marginal distributions of x and y
 (2) Conditional distribution of x given $y = 2$. (8)
- (ii) Find the coefficient of correlation between industrial production and export using the following data. (8)
- | | | | | | | | |
|---------------------|----|----|----|----|----|----|----|
| Production (x): | 55 | 56 | 58 | 59 | 60 | 60 | 62 |
| Export (y): | 35 | 38 | 37 | 39 | 44 | 43 | 44 |

Or

- (b) Given the joint density function of x and y as $f(x, y) = \begin{cases} \frac{1}{2}xe^{-y}; & 0 < x < 2, y > 0 \\ 0 & \text{elsewhere} \end{cases}$. Find the distribution $X+Y$. (16)

13. (a) (i) The process $X(t)$ whose probability distribution under certain

$$\text{condition is given by } P[X(t) = n] = \begin{cases} \frac{(at)^{n-1}}{(1+at)^{n+1}}; & n = 1, 2, 3, \dots \\ \frac{at}{1+at}, & n = 0 \end{cases} \text{ Show}$$

that it is not a stationary process. (8)

(ii) Customers arrive at a grocery store in a Poisson manner at an average rate of 10 customers per hour. The amount of money that each customer spends is uniformly distributed between \$ 8.00 and \$ 20.00. What is the average total amount of money that customers who arrive over a two-hour interval spend in the store? What is the variance of this total amount? (8)

Or

(b) (i) The transition probability matrix of the Markov chain $\{X_n\}$ with

$$n = 1, 2, 3, \text{ having 3 states } 1, 2, 3 \text{ is } P = \begin{pmatrix} 0.1 & 0.5 & 0.4 \\ 0.6 & 0.2 & 0.2 \\ 0.3 & 0.4 & 0.3 \end{pmatrix} \text{ and the initial}$$

distribution is $P^{(0)} = (0.7 \ 0.2 \ 0.1)$. Find $P(x_2 = 3)$ and $P(x_3 = 2, x_2 = 3, x_1 = 3, x_0 = 2)$. (8)

(ii) Find the auto correlation function of random telegraph process. (8)

14. (a) (i) If $X(t) = 5\sin(\omega t + \phi)$, $Y(t) = 2\cos(\omega t + \phi)$ and ϕ is a random variable distributed in $(0, 2\pi)$ where ω is a constant and $0 + \phi = \frac{\pi}{2}$

find $R_{xx}(\tau), R_{yy}(\tau)$ and verify the property that autocorrelation function is an even function of τ . (8)

(ii) Find the spectral density of WSS random process $\{X(t)\}$ whose auto correlation function is $e^{-\frac{\alpha^2 \tau^2}{2}}$. (8)

Or

(b) (i) If $X(t)$ and $Y(t)$ are WSS random processes then prove that $|R_{xy}(\tau)| \leq \sqrt{R_{xx}(0)R_{yy}(0)}$. (8)

(ii) If the power spectral density of a WSS is given by $S(\omega) = \begin{cases} \frac{1}{\alpha}(\alpha - |\omega|) & |\omega| \leq \alpha \\ 0 & |\omega| > \alpha \end{cases}$, find the autocorrelation function of the process. (8)

15. (a) (i) A random process $X(t)$ is the input to a linear system whose impulse response is $h(t) = 2e^{-t}; t \geq 0$. If the autocorrelation function of the process is $R_{xx}(\tau) = e^{-2|\tau|}$, find the power spectral density of the output process $y(t)$. (8)
- (ii) If the input to a time invariant stable line system is a WSS process then prove that the output will also be a WSS process. (8)

Or

- (b) (i) If $y(t)$ is the output process when an input process $x(t)$ is applied to the linear time invariant system with impulse response. The autocorrelation function of the output system is $S_{yy}(w) = |H(w)|^2 S_{xx}(w)$, where $H(w)$ is the system transfer function. (8)
- (ii) A linear time invariant system has an impulse response $h(t) = e^{-\beta t} u(t)$. Find the output autocorrelation function $R_{yy}(\tau)$ corresponding to an input $x(t)$. (8)